

- Cable
- Fibre Optics
- Cable Assemblies
- Connectors
- Racks & Accessories
- Cable Management
- Routers
- Patch Panels
- Mains Distribution
- Audio & Video Monitors

# PRODUCT INFORMATION

SERVING THE BROADCAST INDUSTRY

V1.11

## 14 Way Mains Distribution Unit



### Part Number: HG-00-2014

The Argosy standard 14 way MDU's are designed for the easy installation and safe distribution of mains power within equipment racks. Units are 1RU 19" rack mountable with 14 IEC outputs which are individually fused with power present LED's on the front panel. The unit also features a loop through connector on the rear to allow daisy chaining, however the circuit is limited to 16 amps max at the source. The front panel is made from extruded aluminum, finished in black with a wide Desi strip, a switch guard is also included to prevent unintended operation of the switch.

#### Features

- 14 IEC outlets
- Neutrik PowerCon input and loop connectors
- Front panel accessible fuses, 6 Amp max.
- Green power present LED's on each output
- 2 pole mains input switch
- 110 - 230VAC 50Hz

#### Electrical

- Input Neutrik PowerCon NAC3FCA
- Voltage 110-230VAC
- Frequency 50Hz
- Max current 16A
- Outputs Total load 16A, 6A max per output

#### Mechanical

- 19" rack mount, 1 rack unit high
- 140mm behind panel depth
- Lacing bar at the rear (Max load 10kg)

#### Rear View



 Specifications subject to change without notice. All trademarks are the property of their respective owners.

Argosy Components Ltd (incorporating Argosy-Cable Warehouse) Units 6 & 7 Ridgeway,  
Drakes Drive, Long Crendon, Buckinghamshire HP18 9BF United Kingdom

**ARGOSY**

t: +44 1844 202101

f: +44 1844 202025

www.argosycable.com

e: sales@argosycable.com

